

Preset information

Preset	Description	Occupied addresses
0	8x Turnout magnetic drive without limit switch	8
1	16x On / Off (No effects)	16
2	8x Two-light signal with fade effect	8
3	8x AHOB simulation	8
4	2 groups of 8x fluorescent lighting effect	2
5	1 group of 16x fluorescent lighting effect	1
6	8x Turnout with motor drive with limit switch	8
7	4x Dutch Railway signal	16
8	4x DB Main signal	16
9	4x DB pre-signal associated with main signal	16
10	2x Combination of DB Main signal and pre-signal	8
11	4x DB Pre-signal	16
12	4x Belgian NMBS Signal	16
13	8x Turnout with motor drive without limit switch	8

Address combinations

1st	2nd	3rd	Preset 7	Preset 8	Preset 9	Preset 10 HP	Preset 10 VR	Preset 11	Preset 12
R	R	R	Red	Hp0	Off	Hp0	Off	Vr0	Red
G	R	R	Green	Hp1	Vr0	Hp1	Vr0	Vr1	Red blink
R	G	R	Yellow	Hp2	Vr0	Hp2	Vr0	Vr2	Double Yellow
G	G	R	Green blink with number	Sh1	Off	Sh1	Off	Off	Double Yellow flashing
R	R	G	Yellow with number	Hp1	Vr1	Hp1	Vr1	Vr0	Green-Yellow horizontal
G	R	G	Green-blink	Hp2	Vr1	Hp2	Vr1	Vr1	Green
R	G	G	Yellow-blink	Hp1	Vr2	Hp1	Vr2	Vr2	Green blink
G	G	G	Yellow with dial-blink	Hp2	Vr2	Hp2	Vr2	Off	Green-Yellow vertical